


ADVICE TABLE BATTERY / SOLAR

12 Volt battery energiser
(See also Page 20-21)

Create reliability with a solar panel
(See also Page 24)

Advised battery
(See also Page 20)

Working period (Indication)



12 Volt battery energiser	+	Solar panel	+	Advised battery	Working period	Winter time -/ - 25%
 Powergard XP	+	 20 watt	+	 12V - 110 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 110 Ah Traction battery	21 days 32 days	16 days 24 Dagen
 Powergard	+	 10 watt	+	 12V - 55 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 110 Ah Traction battery	42 days 65 days	25 days 38 days
 Powergard CC	+	 20 watt	+	 12V - 110 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 110 Ah Traction battery	21 days 32 days	16 days 24 days
 PG 200	+	 20 watt	+	 12V - 110 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 110 Ah Traction battery	16 days 25 days	16 days 25 days
 PG 100	+	 10 watt	+	 12V - 55 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 110 Ah Traction battery	25 days 38 days	25 days 38 days
 PG 50	+	 10 watt	+	 12V - 55 Ah Traction battery	Unlimited	Unlimited
	+		+	 12V - 72 Ah 12V - 44 Ah	60 days 36 days	60 days 36 days
 12V Battery devices	+		+	5W Solarkit (12V - 12 Ah accu)	Unlimited	Unlimited